

2 SC 2102	Tos	Si-N	VHF P, 35/18V, 3.5A, 400MHz, PQ>15W(175MHz/12.5V)	55r	SOT-120				BL7 89, MRF 209, 2N5591, 2N6082
2 SC 2103(A)	Tos	Si-N	VHF P, 40/18V, 6A, 300MHz, PQ>24W(175MHz/12.5V) A: PQ>27W(175MHz/12.5V)	55r	SOT-120				BLW 20, BLW 31, 2N6084
2 SC 2104	Tos	Si-N	UHF Drv,Out, 35/17V, 0.8A, PQ=3W(470MHz/12.6V)	55r	SOT-120				2N5945
2 SC 2105	Tos	Si-N	UHF P, 35/17V, 1.4A, >1200MHz, PQ>6W(470MHz/12.6V)	55r	SOT-120				BLW 14, BLW 44, 2N5946
2 SC 2106	Tos	Si-N	UHF P, 35/17V, 2.8A, >900MHz, PQ>12W(470MHz/12.6V)	55r	SOT-120				BLW 15, BLX 69, 2SC1338
2 SC 2107	Nec	Si-N	SMD, 60/40V, 0.1A, 300MHz, 45/440ns	{2SA956	35a	SOT-23	BC 846	35a	BC 846, BCV 71...72, BSR 17, 2SC3361
2 SC 2108	Nec	Si-N	HFS, 120/80V, 0.7A, 0.8W, 250MHz	2a	TO-39				2N2102, 2N2405, 2SC959
2 SC 2109	Nec	Si-N	Uni, 60/40V, 0.2A, 0.3W, 300MHz, 45/400ns	7a	TO-92	BC 546		7a	BC 174, BC 182, BC 546, 2N3903...04, ++
2 SC 2111	Nec	Si-N	S, 40/20V, 0.2A, 0.3W, 500MHz, <20/40ns	7a	TO-92				BSS 11, BSX 19...20, 2N2368...69(A), ++
2 SC 2113	Mat	Si-N	L.F.H.F.S P, 40/30V, 1/2A, 4W, 100MHz	14h	TO-126	BD 139		14h	BD 135, BD 226, BD 375, 2SC 3419, ++
2 SC 2114	Tos	Si-N	UHF A, 15/8V, 0.08A, 0.225W, 7GHz	24f					2SC2876, 2SC3062
2 SC 2115	Tos	Si-N	UHF A, 20/10V, 0.03A, 0.15W, 6.5GHz, Gp=9dB(2GHz)	24f					BFQ 57...58, BFQ 74, 2SC1655...1656, ++
2 SC 2116	Tos	Si-N	UHF A, 30/20V, 0.05A, 0.225W, 3GHz, Gp=15dB(500M)	24f					BFQ 72, BFT 65
2 SC 2117	Tos	Si-N	VHF Drv,Out, 35/17V, 0.8A, PQ=3.2W(175MHz/13.5V)	43a(E=case	=TO-37				-
2 SC 2118	Tos	Si-N	VHF P, 35/17V, 1.4A, PQ=6W(175MHz/13.5V)	43a(E=case	=TO-37				-
2 SC 2119	Tos	Si-N	AM P, 80V, 4A, >100MHz, PQ=6W(28MHz/12V)	17j	TO-220				2SC1816, 2SC2043
2 SC 2120	Tos, Mic	Si-N	Uni, 30/30V, 0.8A, 0.6W, 120MHz	{2SA950	7c	TO-92	BC 639	7c	BC 337...338, BC 635, 2SD1225, 2SD1616, ++
2 SC 2121	Tos	Si-N	S P, 750/300V, 3A, 50W, 8MHz, sat<10V(2.5A)	23a	TO-3	BU 426 A		18j	BU 126, BU 326(A), BU 426(A), 2SD1183
2 SC 2122	Tos	Si-N	TV-HA, 800/325V, 10A, 50W, 6MHz, sat<3.3V(8A)	23a	TO-3	S2530A, 2SD1279		23a	BU 626A, 2SC2123, 2SD1094, 2SD1279
2 SC 2122 A		Si-N	=2SC2122: 1000/400V	23a	TO-3	S2530A, 2SD1279		23a	BU 626A, 2SC2123, 2SD1094, 2SD1279
2 SC 2123		Si-N	TV-HA, 1000/400V, 12A, 50W, 6MHz, sat<3.3V(8A)	23a	TO-3	S2530A, 2SD1279		23a	(BU 626A, 2SD1094, 2SD1279)
2 SC 2124	Tos	Si-N	TV-HA, 2200/800V, 2A, 5W(Tc=90°), sat<10V(1.5A)	23a	TO-3				BU 225, BU 71, 2SD621, 2SD838
2 SC 2125	Tos	Si-N	TV-HA, 2200/800V, 5A, 50W, 5MHz, sat<5V(4A)	23a	TO-3				-
2 SC 2126(A)	Shi	Si-N	S P, 200/200V, 3A, 30W, 36MHz, <1/2.5µs	22a	TO-66				TIP 75(A...C), 2SD422...423
2 SC 2127(A)	Shi	Si-N	S P, 200/200V, 10A, 100W, 33MHz, <1/3µs	23a	TO-3				BUX 17(A...C), BUY 18, TIP 160...162, ++
2 SC 2128(A)	Shi	Si-N	S P, 200/200V, 30A, 200W, 23MHz, <1/3µs	68a					2SC1301, 2SC2249, 2SC2445, 2SC2940, ++
2 SC 2129	Mit	Si-N	=2SC2130: In, Ur<0.3V	7b	TO-92	2SC2632		7c(9mm)	2SC1775(A), 2SC2240, 2SC2390, 2SC2459, ++
2 SC 2130	Mit	Si-N	Uni, 70/70V, 0.1A, 0.2W, 100MHz	7b	TO-92	BC 546		7a	BC 174, BC 190, BC 546, 2SC3245(A), ++
2 SC 2131	Mit	Si-N	UHF Drv,Out, 40/18V, 0.6A, PQ=1.6W(500MHz/13.5V)	2a(E=case)	TO-39				BLX 65, MRF 629, 2SC2762, 2SC3185
2 SC 2132	Mit	Si-N	UHF P, 35/17V, 9A, 1GHz, PQ=30W(470MHz/13.5V)	=57s					BLU 45/12, MRF 648
2 SC 2133	Mit	Si-N	VHF P, 55/35V, 5A, 600MHz, PQ=34W(220MHz/28V)	=57s					-
2 SC 2134	Mit	Si-N	UHF P, 55/35V, 10A, 500MHz, PQ=70W(220MHz/28V)	=57s					MRF 327
2 SC 2135	Son	Si-N	S, sym, 4/4/4V, 0.05A, 0.14W, hFE>500	7e					-
2 SC 2137	Tos	Si-N	S P, 500/400V, 7A, 80W, 6MHz, <-3µs	23a	TO-3	BU 426 A		18j	BUW 34...36, BUX 15, TIP 58A, 2SC3041, ++
2 SC 2138		Si-N	=2SC2137: 400/300V	23a	TO-3	BU 426 A		18j	BUW 34...36, BUX 15, TIP 56A, 2SC3041, ++
2 SC 2139(A)	Tos	Si-N	S P, 500/400V, 10A, 100W, <-3µs	23a	TO-3	BUW 13 A		18j	BUW 24...26, BUW 34...36, 2SC3046, ++
2 SC 2140		Si-N	=2SC2139: 500/350V	23a	TO-3	BUW 13 A		18j	BUW 24...26, BUW 34...36, 2SC3046, ++
2 SC 2141	Son	Si-N	P, 140/140V, 0.5A, 50MHz	{2SA951	13j			17j	2SC1913(A), 2SC2483, 2SC2591...2592, ++
2 SC 2142	Son	Si-N	UHF, 15/15V, 0.03A, 0.165W, 4.5GHz	5g	TO-72				BFQ 22, BFQ 63
2 SC 2143	Son	Si-N	UHF, 15/15V, 0.03A, 0.21W, 4.5GHz	25q	=SOT-103				BFQ 71, BFQ 85, BFR 14
2 SC 2144	Son	Si-N	UHF, 15/15V, 0.02A, 0.21W, 1.4GHz	25p	=SOT-103	2SC2466		25p	2SC2144, 2SC2464, 2SC2466, 2SC2726, ++
2 SC 2145	Mit	Si-N	VHF Drv,Out, 35/18V, 2A, PQ=3.5W(175MHz/13.5V)	2a	TO-39				BFQ 43
2 SC 2147	Sak	Si-N	S P, 400/400V, 50A, 200W, 5MHz, <-3.8µs	68a					2SC2159
2 SC 2148	Nec	Si-N	UHF A, in, 30/14V, 0.05A, 3GHz, F=2, 1dB(500MHz)	51s	SOT-173				BFQ 72, 2SC2844
2 SC 2149	Nec	Si-N	UHF A in, 25/12V, 0.07A, 5GHz, F=2, 6dB(2G)	{2SA1223	51s	SOT-173			BFQ 73, 2SC3302
2 SC 2150	Nec	Si-N	UHF A in, 20/11V, 0.03A, 0.25W, 6GHz, F=2, 4dB(2G)	51s	SOT-173				BFQ 91, BFP 91, BFQ 57...58, BFQ 74
2 SC 2151	Fui	Si-N	S P, 600/400V, 15A, 150W, 15MHz, <-3.3µs	23a	TO-3	BUW 13 A		18j	BUW 13(A), BUW 45...46, 2SD396, 2SD641, ++
2 SC 2152	Mat	Si-N	UHF P, 36/18V, 2/4A, 1.2GHz, PQ=7W(500MHz/13.5V)	56q					-
2 SC 2153	Mat	Si-N	VHF, in, 30/20V, 20mA, >450MHz, F=2/Gp=15dB(200M)	7a	TO-92	BF 959		7d	BF 225, BF 314, BF 502, BF 505, BF 507, ++
2 SC 2159	Sak	Si-N	S P, 400/400V, 50A, 200W, 5MHz, <-2.8µs	68a					2SC2147
2 SC 2160	Fui	Si-N	UHF Drv,Out, 38/18V, 1A, PQ=1.3W(470MHz/12.5V)	2a	=TO-5				BLX 65
2 SC 2161	Fui	Si-N	UHF Drv,Out, 38/18V, 1A, PQ=2.5W(470MHz/12.5V)	55r					BLW 43, BLW 80,
2 SC 2162	Fui	Si-N	UHF P, 38/18V, 2A, 1GHz, PQ=5W(470MHz/12.5V)	55r					BLW 14, BLW 44, 2N5946
2 SC 2163	Fui	Si-N	UHF P, 45/25V, 5A, 800MHz, PQ=15W(470MHz/12.5V)	55r					BLW 15, BLX 69, 2SC1338...1339,
2 SC 2164	Fui	Si-N	UHF P, 45/25V, 10A, 700MHz, PQ=30W(470MHz/12.5V)	57s	SOT-119				BLU 45/12, MRF 646, 2SC2783
2 SC 2165	Hit	Si-N-Darl+Di	S, 120/120V, 5/10A, 0.8W, hFE=1000, 400/4000ns	5	TO-33				2SC1882
2 SC 2166	Mit	Si-N	H F, 75V, 4A, PQ=6W(27MHz/12V)	17j	TO-220	2SC2166		17j	2SC1944, 2SC1969, 2SC2043, 2SC2119, ++
2 SC 2167	Sak	Si-N	P, 150/150V, 2A, 30W, 20MHz, <-3.5µs	{2SA957	17j	TO-220	2SD1138	17j	BD 2390, 2SC2529, 2SC2660, 2SD1138, ++
2 SC 2168		Si-N	=2SC2167: 200/200V	{2SA958	17j	TO-220	2SD1138	17j	BD 239F, 2SC2660, 2SD760, 2SD1138, ++
2 SC 2169	Fui	Si-N	VHF P, 36/33V, 4A, 25W, PQ=9W(175MHz/12.5V)	61s	SOT-171				-
2 SC 2172	Nec	Si-N	SMD, 60/45V, 0.2A	35a	SOT-23				BCW 65...66, 2SC2882
2 SC 2173	Tos	Si-N	UHF P, 35/18V, 6A, 400MHz, PQ=28W(470MHz/12.6V)	55r	SOT-120				-
2 SC 2174	Nec	Si-N	UHF, 25/12V, 0.07A, 4.5GHz, F=2, 7/Gp=6.5dB(2GHz)	52s	SOT-100				BFP 96, 2SC2844, 2SC3302
2 SC 2175	Mit	Si-N	S P, 350/350V, 10A, 100W	23a	TO-3	(BUW 13A)		18j	BUW 24...26, BUW 34...36, 2SC2625...26, ++
2 SC 2176	Tos	Si-N	VHF P, 50/25V, 3A, >200MHz, PQ=12W(270MHz/20V)	55r	SOT-120				BLX 95, 2SC2894
2 SC 2177	Tos	Si-N	VHF P, 50/25V, 5A, >200MHz, PQ=22W(270MHz/20V)	55r	SOT-120				2N6105
2 SC 2178	Tos	Si-N	VHF P, 35/18V, 3.5A, 400MHz, PQ>15W(175MHz/12.5V)	59r	SOT-121				MRF 222...223
2 SC 2179	Fui	Si-N	UHF P, 55/40V, 6A, PQ=40W(770MHz/24V)	55r					-
2 SC 2180	Tos	Si-N	VHF P, 35/18V, 6A, PQ=27W(175MHz/13.5V)	55r	SOT-120				BLW 20, BLW 31, 2N6084
2 SC 2181	Tos	Si-N	VHF P, 35/18V, 10A, 300MHz, PQ>40W(175MHz/13.5V)	59r	SOT-121				BLW 85
2 SC 2182	Tos	Si-N	VHF P, 65/35V, 6A, 150MHz, PQ=50W(175MHz/28V)	55r	SOT-120				BLY 94
2 SC 2183	Tos	Si-N	UHF P, 35/18V, 4.5A, 400MHz, PQ=16W(470MHz/12.6V)	55r	SOT-120				BLW 15, BLX 69, 2SC1404, 2SC1338
2 SC 2184	Fui	Si-N	AM P, 60/60V, 3A, 200MHz, PQ=5W(27MHz/12V)	17j	TO-220				2SC1306, 2SC1816, 2SC1909, 2SC2092
2 SC 2185	Nec	Si-N	VHF/UHF P, 50/25V, 6A, >160MHz, PQ=30W(275MHz/18V)	57s	SOT-119				2SC2796, 2SC2895
2 SC 2186	Nec	Si-N	VHF/UHF P, 50/25V, 9A, >110MHz, PQ=60W(275MHz/18V)	57s	SOT-119				MRF 327
2 SC 2188	Mat	Si-N	VHF, TV IF, 45/35V, 50mA, 500MHz, Gp=18dB(58MHz)	9c		BF 198, BF 199		7d	BF 225, BF 310, BF 314, BF 502...503, ++
2 SC 2189	Fjd	Si-N	S P, 150/100V, 10A, 80W, <1/4µs	23a	TO-3	2SC3263		18j	BD 245D, BDX 11, 2N3442, 2SD551, ++
2 SC 2190	Fjd	Si-N	S P, 450/400V, 5A, 100W, <1/5.3µs	23a	TO-3				BUW 71, BUX 45, TIP 57A...58A, 2SC3040, ++
2 SC 2191	Fjd	Si-N	S P, 450/400V, 10A, 100W, <2/5.2µs	23a	TO-3				BUW 72, BUW 75, BUX 14, 2SC3520, ++
2 SC 2192	Mat	Si-N	VHF P, 36V, <-5A, 600MHz, PQ>15W(175MHz/13.5V)	56q					-
2 SC 2193	Oki	Si-N	Uni, 150/120V, 0.3A, 0.6W, 150MHz	2a	TO-39	(MPS-U10) <sup>6</sup>		13m	2SD413, 2SD624, (BF 380, MPS-U10) <sup>6</sup>
2 SC 2194(A)	Tos	Si-N	Uni P, 60/50V, 1.5A, 100MHz	{2SA962	13m	A: TO-202	(2SC4135) <sup>4</sup>	30j	BD 517, BD 519, BD 525, BD 527, BD 529
2 SC 2196	Fui	Si-N	VHF Drv,Out, 40/18V, 2A, PQ=4.8W(175MHz/12.5V)	2a(E=case)	TO-39				(2SC2145)
2 SC 2197	Fui	Si-N	VHF P, 50/25V, 6A, 500MHz, PQ=30W(160MHz/13.5V)	55r	SOT-120				BLW 20, BLW 31, 2N6084
2 SC 2198	Sak	Si-N	100/50, hi-Ueb=15V, 6/10A, 40W, 17MHz, hi-hFE=300	22a	TO-66				(2SC2316, 2SC2491)
2 SC 2199	Sak	Si-N	150/80V, hi-Ueb=15V, 8A, 60W, 12MHz, hi-hFE=300	23a	TO-3				-
2 SC 2200	Tos	Si-N	S P, 500/400V, 7A, 40W, <-3µs	22a	TO-66	BUT 56 A		17j	BUT 56(A), 2SC2235, 2SC2427, 2SC3039, ++
2 SC 2204	Tos	Si-N	S P, 800/400V, 30A, 250W, <1.5/5µs	68a					2SC2977, 2SD295
2 SC 2205	Nec	Si-N	Dual, 45/25V, 0.03A, 0.4W, 2.2GHz, aUbc<30mV	TO-71/6Pin	(ECBBCE)				-
2 SC 2206	Mat	Si-N	AM/FM, Uni, in, 30/20V, 0.03A, 0.4W, 300MHz	{2SA1254	9c	(M Type)	BC 546, BF 255	7a, 7d	BC 238, BC 548, BF 240...41, BF 254...55, ++
2 SC 2207	Hit	Si-N	AM P, 80/50V, 8A, 200MHz, PQ=14W(27MHz/1						